

6808U ULTRA SERIES

Intelligent Fire Alarm Control Panel with Communicator

The 6808U features a built-in SLC circuit, eight Flexput® circuits, dual-line DACT, powerful software features, and connectivity for up to 17 panels.

The 6808U is the latest intelligent addressable FACP (Fire Alarm Control Panel) from Silent Knight and is a direct replacement for the 6808/5808 FACP. The 6808U has one SLC (signaling line circuit) loop for connecting addressable detectors, which can support 159 System Sensor® SK sensors and 159 SK modules or 127 Hochiki® SD devices per loop.

A common communications and annunciation link allows up to 17 panels to be connected via copper wire or fiber optic cable. A designated panel is configured as the communicator for all panels in the link for convenient single-point communications.

The built-in digital alarm communicator/transmitter (DACT) is dual technology, IP and POTS. The POTS transmits system status (alarms, troubles, AC loss, etc.) to a Central Station via the public switched telephone network. The IP communicator's internet monitoring capability sends alarm signals over the Internet saving the monthly cost of two dedicated business telephone lines. Although not required, the secondary telephone line may be retained providing backup communication over the public switched telephone line. Optional cellular reporting is available.

The 6808U has eight onboard Flexput® circuits that can be configured as notification outputs or auxiliary power. There are four types of Aux power available: door holder, constant power, resettable power and sounder sync power. The 6808U also has form-C trouble relay, and two programmable form-C relays, along with powerful features such as drift compensation, pre-trouble maintenance alert, a built-in sensor test to comply with NFPA 72 calibration testing requirements, and a calibration trouble alert.

The 6808U supports a variety of devices, including 6860, 5860, or 6855 remote annunciators, 5824 serial/parallel printer interface modules (for printing system reports), 5895XL power modules, and SK, SWIFT® wireless, or SD devices.



FEATURES AND BENEFITS

- Complies with UL 864 10th Edition
- Built-in support for up to 159 IDP/SK detectors and 159 IDP/SK modules or 127 SD SLC devices
- Eight Flexput circuits (3 amps max) for NAC outputs or auxiliary power
- Selectable strobe synchronization for Amseco®, System Sensor, Wheelock®, and Gentex® devices
- 999 software zones and 999 output groups for flexible design options
- Built-in dual phone line, digital alarm communicator/ transmitter (DACT) with IP and optional cellular technologies
- Four line LCD display with 40 characters per line
- Built-in USB interface for quick and easy programming
- JumpStart® auto programming reduces installation time
- 23 preset notification cadence patterns (including ANSI® 3.41)
- Allows up to 20 SBUS devices
- Two programmable relays and one fixed trouble relay
- Convenient field-upgradeable firmware
- Supports up to four SWIFT wireless gateways which can foster up to 49 wireless devices each
- Connectivity for up to 17 sites
- Network card allows copper network connection with a multi-mode or single-mode fiber connection
- Programmable date setting for Daylight Savings Time
- History file with 1,000 event capacity
- Can be surface or flush-mounted



USER INTERFACE

LED INDICATORS

- General Alarm (Red)
- Supervisory (Yellow)
- System Trouble (Yellow)
- System Silenced (Yellow)
- System Power (Green)

KEYPAD

- 12-key numeric pad
- Acknowledge
- Alarm Silence
- System Reset
- F1-F4 Programmable Function Keys

PROGRAMMING

The 6808U system offers several options to simplify and expedite programming. JumpStart auto programming minimizes programming required to start a new system. The built-in keypad, or the remote annunciators give on-site access to current system programming. System programming can also be accomplished using the Windows®-based Honeywell Fire Software Suite (HFSS).

ORDERING INFORMATION

6808U: Addressable fire alarm control panel, red

COMPATIBLE SBUS DEVICES

- 6860: 4x40 LCD remote fire annunciator with four programmable buttons, red
- 5860: 4x20 LCD remote fire annunciator, gray
- 5860R: 4x20 LCD remote fire annunciator, red
- 6855: 4x20 LCD remote fire annunciator, red
- 5880: LED I/O module with 40 programmable LED outputs and eight supervised dry contact inputs
- 5883: Relay interface. Provides 10 Form C relays
- 5824: Serial/Parallel printer interface module for printer connection

SK AND SS COMPATIBLE ADDRESSABLE DEVICES

Note: SK/SS and SD devices cannot be mixed in the same system. Refer to the *Device Compatibility Document* and *SLC Wiring Manual* for more information.

- SK-ACCLIMATE: Multi criteria photoelectric smoke detector with thermal 135°F fixed temperature
- SS-CO: Carbon Monoxide detector
- SS-PHOTO-CO: Photo/CO Detector
- SS-FIRE-CO: Fire/CO Multi-criteria Detector
- SS-HEAT-HT: High temp (190°F) heat detector w/ base
- SS-HEAT-ROR: Fixed/Rate-Of-Rise heat detector w/ base
- SS-HEAT: Fixed temp (135°F) heat detector w/ base
- SS-PHOTO-R: Photo detector with remote test
- SS-PHOTO-T: Photo/thermal detector w/ base
- SS-PHOTO: Photo detector w/ base
- SS-PTIR: Photo/Thermal/IR detector w/ base
- OSI-RI-SK: Reflected beam smoke detector, SK protocol
- SK-CONTROL: Supervised control module

- SK-CONTROL-6: Six circuit supervised control module
- SK-FIRE-CO-W: Four element fire and carbon monoxide detector, white
- SK-HEAT-W: Fixed thermal detector (135°F), white
- SK-HEAT-HT-W: Fixed high temperature thermal detector (190°F), white
- SK-HEAT-ROR-W: Fixed rate of rise detector, white
- SK-ISO: Fault isolator module
- SK-MINIMON: Mini monitor module
- SK-MONITOR: Monitor module
- SK-MONITOR-2: Dual input monitor module
- SK-MONITOR-10: 10- input monitor module
- SK-PHOTO-W: Photoelectric smoke detector, white
- SK-PHOTO-R-W: Photoelectric detector with remote test capability for DNR/DNRW duct detector, white
- SK-PHOTO-T-W: Photoelectric smoke detector with fixed thermal heat (135°F), white
- SK-PTIR-W: Multi criteria photoelectric smoke detector with thermal 135°F fixed temperature, white
- SK-PULL-SA Addressable single action pull station
- SK-PULL-DA: Addressable dual action pull station
- SK-RELAY: Addressable relay module
- SK-RELAY-6: Addressable Six relay control module
- SK-RELAYMON-2: Addressable Dual relay/monitor module
- SK-ZONE: Addressable zone interface module
- SK-ZONE-6: Six zone interface module

SK BASES

- B210LP: 6" mounting base
- B501: 4" Flangeless mounting base
- B200S: Intelligent sounder base
- B200S-LF: Low-frequency intelligent sounder base
- B224RB: Relay base
- B224BI: Isolator base

SD COMPATIBLE ADDRESSABLE DEVICES

Note: SK and SD devices cannot be mixed in the same system.

- SD505-6AB: Addressable 6" base
- SD505-6IB: Addressable 6" short circuit isolator base
- SD505-6RB: Addressable 6" relay base
- SD505-6SB: Addressable 6" sounder base
- SD500-AIM: Addressable input module (switch input)
- SD500-ANM: Addressable notification module
- SD500-ARM: Addressable relay module
- SD505-DTS-K: Remote test switch/LED indicator for the SD505-DUCTR
- SD505-DUCT: Addressable Duct Smoke Detector
- SD505-DUCTR: Addressable Duct Detector housing with relay base
- SD505-HEAT: Absolute temperature heat detector. Trip point range from 135°F–150°F (57.2°C–65.6°C)
- SD500-LIM: Addressable Line isolator module
- SD500-MIM: Addressable Mini input monitor module (switch input)
- SD505-PHOTO: Photoelectric smoke detector
- SD500-PS/-PSDA: Addressable Single or dual action pull station

SD500-SDM: Addressable smoke detector module

SWIFT WIRELESS DEVICES

Note: SWIFT is only compatible with System Sensor (SK) devices. It is not compatible with Hochiki (SD) devices.

WSK-WGI: Wireless gateway

WSK-PHOTO: Wireless photoelectric smoke detector with B501W base

WSK-PHOTO-T: Wireless photoelectric smoke detector with fixed thermal detection (135°F) and B501W base

W-SYNC: Wireless sync module

WSK-HEAT: Wireless, fixed heat detector (135°F) with B501W base

WSK-HEAT-ROR: Wireless rate-of-rise heat detector and B501W base

WSK-MONITOR: Wireless monitor module

WSK-RELAY: Wireless relay module

WSK-PULL-DA: Wireless pull station

WAV-CRL, WAV-CWL: Wireless AV bases

W-USB: Wireless USB radio/antenna dongle that plugs into the USB port of a PC running SWIFT Tools

SWIFT Tools: Programming and diagnostic utility for the wireless gateway and devices. Available for download from www.farenhyt.com

SYSTEM EXPANDERS

5895XL: 6A power supply with six Flexput circuits and two Form C relays

5496: 6A NAC power expander with four power-limited output circuits

OPTIONAL COMMUNICATORS

HW-AV-LTE-M-2: CLSS Pathway, Fire Alarm Dual Path Communicator, LTE Dual SIM, includes antenna, ETL & UL Listed.

MISCELLANEOUS ACCESSORIES

HW-AV-ENC2-PS: 120V Power Supply with Metal Enclosure for CLSS Pathway (HW-AV-LTE-M-2 sold separately)

SK-NIC: Network Interface Card. Provides a common communications link for the SK SKUS 6808/6820/6820EVS

SK-NIC-KIT: Network Interface Card mounted in enclosure

SK-FML: Fiber Optic Multi-mode Networking Card

SK-FSL: Fiber Optic Single-mode Networking Card

RBB: Remote battery box accessory cabinet

SK-SCK: Seismic compliance kit to fasten batteries to the fire panel

SOFTWARE SOLUTIONS

SKST: Silent Knight Selection Tool provides the installer or design architect with a Windows®-based software system configuration tool to create a detailed bill of material (BOM) and battery calculations

HFSS: Honeywell Fire Software Suite provides remote and local panel programming, detector status, event history and additional data. Databases can be uploaded/downloaded via the panel's USB port using a flash drive. Requires a PC running Microsoft® Windows®.

6808U ULTRA SERIES TECHNICAL SPECIFICATIONS

SYSTEM CAPACITY

Intelligent Signaling Line Circuits: 1
Addressable device capacity: 318 (SK) or 127 (SD)
Programmable software zones: 999
Output circuits: 8 (expandable)
SBUS Devices: 20 (12 annunciators, 8 LED modules)

ELECTRICAL

AC Power: 120 VAC, 60 Hz, 5 A or 240VAC, 50/60Hz 2.8A
Standby Current: 230 mA
Alarm Current: 415 mA
Flexput Circuits: Terminal block provides connections for (8 Class B or four Class A) NACs or auxiliary power. Power-limited, supervised circuitry. Maximum current per circuit: 3 A. Cannot exceed 9A total for all circuits. End-of-line resistor: 4.7k ohm, ½ watt for Class B NACs
Communication Loop: Supervised and power-limited, Class A or Class B, 32VDC, 150mA
Two Programmable Relays and One Fixed Trouble Relay: Contact rating: 2.5 A @ 27.4 VDC (resistive), Form C
Battery: Cabinet holds maximum of two 18 AH batteries
Battery Charger Capacity: 17-55 AH

PHYSICAL

Dimensions: 16.4" W x 26.4" H x 4.1" D
(41.66cm W x 67.06cm H x 10.41cm D)
Weight: 45 lbs. (20.4 kg).
Color: Red

TEMPERATURE AND HUMIDITY RANGES

This system meets NFPA requirements for operation at 0 – 49°C (32– 120°F) and at a relative humidity 93% ± 2% RH (non-condensing) at 32°C ± 2°C (90°F ± 3°F). However, the useful life of the system's standby batteries and the electronic components may be adversely affected by extreme temperature ranges and humidity. Therefore, it is recommended that this system and its peripherals be installed in an environment with a normal room temperature of 15 – 27°C/60 – 80°F.

NFPA STANDARDS

The 6808U complies with the following NFPA 72 Fire Alarms Systems requirements: NFPA 13, NFPA 15, NFPA 16, NFPA 70, NFPA 72

Central station; remote Signaling; Local Protective Signaling Systems; Auxiliary Protected Premises Unit; Water Deluge releasing service. Suitable for automatic, manual, waterflow, sprinkler supervisory (DACT non-coded) signaling services

AGENCY LISTINGS AND APPROVALS

UL Listed: S2766
CSFM: 7165-0559:0523
FDNY: COA# 6246
FM Approved
Seismic: (CA) VMA-45894-05C

Flexput®, Honeywell®, JumpStart®, Silent Knight®, SWIFT®, and System Sensor® are registered trademarks of Honeywell International Inc. Amseco® is a registered trademark of Potter Electric Signal Company, LLC. Gentex® is a registered trademark of Gentex Corporation. Hochiki® is a registered trademark of Hochiki Corporation. Wheelock® is a trademark of Cooper Technologies Company. ANSI® is a registered trademark of the American National Standards Institute, Inc. VisorALARM® is a registered trademark of the Teldat Corporation. Microsoft® and Windows® are registered trademarks of Microsoft Corporation.

This document is not intended to be used for installation purposes. We try to keep our product information up-to-date and accurate. We cannot cover all specific applications or anticipate all requirements. All specifications are subject to change without notice.

Country of origin: USA