



All dimensions shown are in millimetres

All steel construction: **dia 22mm horizontal tubes**
D profile 30mm x 40mm headers

Connections: **1.2m long flying lead (2 core)**

* does not include immersion heater

Model	Height* ± 2mm	Width ± 2mm	Finish	Output Watts	Weight kg
PBEZ-080-40/F	786	400	painted	300	7.9
PBEZ-090-50/F	906	500	painted	500	10.8
PBEZ-120-50/F	1226	500	painted	750	15.3
PBEZ-120-60/F	1226	600	painted	750	17.2
PBEZ-150-60/F	1466	600	painted	1000	20.0
PBEZ-180-50/F	1866	500	painted	1000	22.3
PBECZ-080-40/F	786	400	chrome	150	7.9
PBECZ-090-50/F	906	500	chrome	200	10.8
PBECZ-120-50/F	1226	500	chrome	300	15.0
PBECZ-120-60/F	1226	600	chrome	400	17.1
PBECZ-180-50/F	1866	500	chrome	500	22.1
PBECZ-120-50/MF	1226	500	chrome	300	15.2
PBECZ-120-60/MF	1226	600	chrome	400	17.3

Issue 1.0



Tools & Material Required

Tape measure
Electric drill
Masonry drill bit - 10mm diameter
Spirit level
Stepladder (for taller radiators)

Key	Component	Qty
A	Wall Plug	4
B	Bracket	4
C	Screw - 6mm dia x 50mm	4
D	Washer	4
E	Inner Clamp	4
F	Outer Clamp	4
G	Csk Screw	4
H	Cover Cap	4
I	Grub Screw	4
J	Allen Key	1

Assembly Instructions

Accurately mark out bracket holes on wall using spirit level.

Drill four 10mm diameter holes to a minimum depth of 65mm & insert wall plugs (A).

Screw brackets (B) into wall plugs (A) with screws (C) & washers (D).

Loosely fit inner clamps (E) and outer clamps (F) to rungs of radiator using countersunk screws (G).

Offer radiator up to wall and slide inner clamps (E) into brackets (B).

Adjust radiator to desired projection from wall and secure in position by tightening grub screws (I) with allen key (J).

Push cover caps (H) into outer clamps (F).

Electric radiators should be fitted only by a qualified electrician and must be earthed and connected to a cable outlet in the bathroom in accordance with I.E.E. wiring regulations. The electrical connection should be made to a '5 amp fused fixed spur' located outside the bathroom.

Note: for maintenance purposes, cable outlets must remain accessible and cables must not be buried directly into walls.

