



SDACT-2 Serial Dialer and Digital Communicator



SDACT-2 Shown without the
SDACTBX-GRAY Metal Housing

ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The Serial Dialer Unit unit(s) shall be Alpha Communications® / Keltron model **SDACT-2**, or approved equal. The **SDACT-2** shall be used in conjunction with an Alpha Communications® Emergency-Call (or similar) notification system, to allow alarm indication at an on- or off-site central station monitoring location.

The **SDACT-2** shall have an RS232 port that will allow a string of RS232 data to be converted to an industry standard SIA format for alarm event reporting. Unit shall also be provided with 2 SPDT relays for common alarm and common trouble indication.

The **SDACT-2** shall be mountable right to the surface of the wall when mounted in a the **SDACTBX-GRAY** junction box cabinet, and shall require a customer supplied external phone line and jack.

Contractor shall observe all local and national electrical and building codes.

SUPPORTED INTERFACES

97P1411SD2:	COMP2 protocol @ 9600 baud - data derived zone number - event code fixed to Medical Alert (MA)
97P1412SD2:	COMP2 protocol @ 2400 baud - data derived zone number - event code fixed to Medical Alert (MA)

SDACT-2 SERIAL DIALER AND DIGITAL COMMUNICATOR

The Alpha Communications® / Keltron **SDACT-2** is a unique solution that interfaces with emergency-call, access control, building management and other systems to enable an appropriate and instantaneous response from personnel at a central or remote monitoring location. The **SDACT-2** provides a bridge to an on- or off-site central station-style digital receiver through the dial-up public switched telephone network (PSTN).

The **SDACT-2** accepts pre-defined ASCII RS232 data strings and converts to SIA, a standard, digital receiver-compatible, alarm reporting format.

The most common applications for the **SDACT-2** is for use with our **AlphaEntry®** and **AlphaEcall™** 200 series emergency-call systems and devices, although it can be used with other similar systems.

FEATURES

- RS232 Port enables accurate monitoring of event type and location identification
- Test code call-in cycles are programmable. A manual test button is also included
- Transmits signals in industry standard SIA format
- Works with a variety of alarm notification equipment
- Zones 1-4 supervised EOL, suitable for fault-contact monitoring
- Zones 5-7 are available for loss of AC and battery fail indications, which are also reported using standard SIA event codes
- Local LEDs and audible devices clearly indicate Serial Dialer status

SPECIFICATIONS

Dimensions (in SDACTBX-GRAY Housing):	Height: 14.00" (356mm) Width: 17.00" (432mm) Depth: 4.00" (102mm) from mounting surface
Phone Lines:	2 RJ45 receptacles. Line seizure via RJ31x jack (by others)
Hardwired Zone Inputs:	7 (4-EOL resistor supervised). EOL resistor value 10K Ohms.
Audible Device:	rated at 92DB

97P1413SD2:	COMP2 protocol @ 9600 baud - data derived zone number - event code fixed to Burg (BA)
97P1414SD2:	COMP2 protocol @ 9600 baud - data derived zone and event code
97P1414SD2:	Hybrid protocol @ 9600 baud - data derived zone number - fixed Medical Alert (MA) event code or derived Fire Alarm (FA) event code
97P1501SD2:	Universal Serial Interface Protocol @ 9600 baud - supervised SIA or Contact-ID data protocol - data derived zone and event code

SPECIAL INSTALLATION NOTE

The **SDACT-2** serial dialer is typically installed adjacent or nearby to the **AlphaEntry®** PC Master station or the **AlphaEntry™** 200 series Master station. If the **SDACT-2** needs to be mounted in a remote location, a distance away from the USB port on the PC Master, the installer will need to provide a compatible serial extension cable/device.

Ringer Equivalence:	.1
FCC Reg.# US:	KELAL00BSDACT-2
User Controls:	Jumper (8 total) and Pushbuttons: Reset, Manual Test, Silence, Program.
Power Requirements:	Power Input - regulated or unregulated, filtered 20.4 to 27.5VDC
Power Draw:	75mA Idle, 200mA all alarm or lamp test
Programming and Monitoring Port:	DB-9F RS-232

Alpha Communications

42 Central Drive • Farmingdale • NY • 11735-1202 • Phone: (631) 777-5500 • Fax: (631) 777-5599
TOLL-FREE: (800) 666-4800 • Web: www.alphacommunications.com • Email: info@alphacommunications.com

Copyright© 1998-2023 Alpha Communications® - All Rights Reserved.

Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.