



ALARM.COM®

1080p Outdoor Wi-Fi Camera with HDR and Two-Way Audio Data Sheet

ADC-V724X

www.alarm.com

© 2021 Alarm.com. All rights reserved. 210402

Specifications

Image sensor: 1/3", 2 MP, 1920x1080, HDR

Recording Compression: H.264

Live resolution options: Up to 1920 x 1080

Recording resolution options: Up to
1920 x 1080

Horizontal Field of View: 117 degrees

Vertical Field of View: 65 degrees

Diagonal Field of View: 140 degrees

Wi-Fi: 802.11 support: b/g/n/ac, 2.4 & 5 GHz

Ingress Protection: IP66

Low Light Sensitivity: 0.5 lux with IR

IR Range: Up to ~49 ft (15 m)

Image adjustments: Flip, brightness,
contrast, saturation, sharpness, exposure

Operating Humidity: 20%-100%
(non-condensing) RH

Dimensions (L x W x H): 2.5 x 2.5 x 4.5"
(6.35 x 6.35 x 11.43 cm)

Requirements

Power: 12 V – 1 A DC power adapter
(included)

Network: Wi-Fi (2.4 or 5 GHz) connection to
broadband Internet



Overview

The ADC-V724 is Alarm.com's first outdoor camera with Two-Way Audio, allowing for proactive deterrence of unwanted activity on a customer's property. Powerful Video Analytics from Alarm.com can detect and alert customers to people and animals active around their homes or businesses. Two-Way Audio gives your customers the power to discourage unwanted visitors. Plus, thanks to Onboard Recording with Smart View your customers can locally record encrypted video onto a microSD (sold separately) and view footage from anywhere.

Included accessories

- Power adapter
- Installation guide

Features

- Two-Way Audio to hear and speak with visitors
- Microphone and speaker
- Video Analytics for smarter detection and relevant alerts
- Onboard Recording with Smart View for continuous, local, encrypted recordings
- High Dynamic Range (HDR)
- Wi-Fi (2.4 or 5 GHz)
- Audio included in recorded clips for additional awareness
- Works with the Alarm.com Customer Website and Mobile App
- Improved mount for long-term stability
- Easier access to microSD card door

LED Guide

Status LED	
	Power off
	Power on, camera booting
	Local network connection
	Connected to Alarm.com
	WPS Mode
	Wi-Fi Access point mode
Trouble Condition 	No local or internet connection
Factory Reset 	Camera resetting to factory default