

One and Two-Channel RF Receivers

SK-910RBQ	315MHz, 1 Channel
SK-910RB2Q	315MHz, 2 Channel
SK-910R-4Q	433.92MHz, 1 Channel
SK-910RB2-4Q	433.92MHz, 2 Channel

Features:

- Five programmable relay output modes:
 - 4-Second momentary
 - 1-Second momentary
 - Toggle (ON/OFF)
 - Validity
 - Latch†
- 11~24 VAC/VDC Operation
- Range: Up to 500ft (150m)*
- Controls garage doors, gates, house lights, alarm panels or other devices via remote
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode
- Pushbutton programming, no need to cut jumpers‡
- Up to 15 transmitter button codes can be learned



SK-910RBQ / SK-910R-4Q



SK-910RB2Q / SK-910RB2-4Q



Specifications:

Model		SK-910RBQ	SK-910RB2Q	SK-910R-4Q	SK-910RB2-4Q
Operating frequency		315MHz			433.92MHz
Memory capacity		15 transmitter button codes per channel			
Operating voltage		11~24 VAC/VDC			
Operating current	Standby	8mA@12VDC			
	Active	30mA@12VDC per channel			
Relay contact rating		Form C 10A@24VDC per channel			
Connectors		Screw terminals, +,-, with NO/NC/COM per channel			
Dimensions		3 1/8"x2 9/16"x1" (80x65x25 mm)		3 1/4"x2 11/16"x1 1/16" (83x68x27.5 mm)	

*Operating range will vary greatly depending on the installation and operating environment.

†Special order item. Contact SECO-LARM for more details.

‡SK-910RBQ, SK-910RB2Q, and SK-910RB2-4Q only

Compatible Transmitters:

Model	315MHz		
	CODEBUMP™	68 Billion Codes	
	Pendant		Handheld
SK-910RBQ	SK-917T1-GBQ SK-917T2-GNQ SK-917T3-GNQ† SK-917T4-GNQ	SK-919T1-GBQ SK-919T1-GBUQ SK-919T2-GNQ SK-919T3-GNQ SK-919T4-GNQ	SK-919TP1H-BQ SK-919TP2H-NQ SK-919TP4H-NQ
SK-910RB2Q			
433.92MHz Pendant 68 Billion codes			
SK-910R-4Q	SK-939T1-GBUQ SK-939T2-GNUQ SK-939T3-GNQ† SK-939T4-GNQ†		
SK-910R2-4Q			

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Copyright © 2020 SECO-LARM U.S.A., Inc. All rights reserved.

All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners. The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA® SLI®

PI_RF-Receivers_200323.docx